

JX-03 Vintage Dream Bank I			
Patch Number	Patch	Name	Type
C1	JX03_PATCH1	Fender Bass 01	Bass
C2	JX03_PATCH2	Abacab	Brass
C3	JX03_PATCH3	Vangelis Chart	Pad
C4	JX03_PATCH4	Cristal Brass	Lead
C5	JX03_PATCH5	Celest Harp	Hschord
C6	JX03_PATCH6	Daftbass	Basse
C7	JX03_PATCH7	Long Celest Pad	Pad
C8	JX03_PATCH8	Short Celest Pad	Pad
C9	JX03_PATCH9	Police Sirens	FX
C10	JX03_PATCH10	Vibrapad	Pad
C11	JX03_PATCH11	Brass string	Brass
C12	JX03_PATCH12	Organ Slow Leslie	Organ
C13	JX03_PATCH13	PWM bass 02	Bass
C14	JX03_PATCH14	Celest Pad 02	Pad
C15	JX03_PATCH15	Third Time	Lead
C16	JX03_PATCH16	PadOrgan	Pad

Copyright ©Studio LVdkh - L.Vandenkoornhuyse 2019

**To mount the JX-03 to your desktop follow this procedure:**

1. Holding down the 2 button, power up the JX-03
2. Connect your computer to the JX-03 USB port via USB cable
3. Open the JX-03 drive which has mounted to your desktop

**To create a backup of your patches:**

1. Follow the above procedure for mounting the JX-03
2. Copy the backup files from the JX-03 drive into an appropriately named folder on your computer
3. Once you're done, eject the JX-03 drive, disconnect the USB cable and you're done.

**To bring patches from your computer into the JX-03:**

1. Follow the above procedure for mounting the JX-03
2. Copy the backup files, or the new patches you'd like to check out into the "RESTORE" folder on the JX-03 drive
3. When copying is completed, eject the JX-03 drive.
4. IMPORTANT - Before power cycling the module press the MANUAL button
5. Once the lights stop blinking you may power cycle the JX-03 and disconnect the USB cable and you're done.